


SPECIFICATION

Notice:

- *Please make sure the controller over against the clock.
- *Control range is 10M.
- *Neon maybe have a influence on controller.
- *Keep away from the Neon.


On/off:

- *Open and close the display board.
- *  Power on/off key. Controller doesn't work when clock is off.


Display help:

- *Clock is power on when connect to the electric power.
- *Time display: Hour & minutes.
- *Date display: Month & day.
- *Temperature: centigrade(C) & Fahrenheit(F).
- *SCAN(recycling shows): Press **DISP** key 3 times at the same time, then the clock will display from DATE to Temp to Time.
- *Press **DISP** key 1 time can stop SCAN.
- *Alarm rings: Rings for 1 minutes from slow to fast or press **ALON/OFF** key to stop.

User browsing pattern:

- *Press  key to see Time Temp and Date display.
- *Press **A1 A2 A3 A4 A5 A6** to see the alarms time, display by Hour & minutes.

Time display and setting:

- *Press **12/24(0)** key to change time display from AM/PM.
- *Press **TSET** key get into time setting. Use **UP/DOWN** or (0~9) Key5 to change the number which is flashing and press **MODE** key to move to the next position.
- ***HOUR & MINUTE & SECOND** are in turn.
- *After setting, press **RET** or  to exit.

Temperature display setting:

- ***C/F** key: press this key to change the display mode of temperature from C & F.



Calendar setting:

Press **CSET** key get into calendar setting. Use **UP/DOWN** or (0~9) key to change the number which is flashing and press **MODE** key to move to the next position. **YEAR MONTH & DAY** are in turn.

Alarm setting:

*Press **ALSET** key get into alarm setting. There are 6 groups of alarms (AL 01~AL 06)

1. Two digits are flashing on the right, use **UP/DOWN** key to choose which alarm you want to set.

Take an examples AL 01.

Press **ALSET** key and use **UP/DOWN** key or 0~9 key to choose AL 01, then press **MODE** key and continue setting. Two digits on the right are flashing, that is **HOUR**, use **UP/DOWN** key or 0~9 key to choose a number you want and press **MODE** key to next 1.

Next 1, the two flashing digits are **MINUTES**, use **UP /DOWN** key or 0~9 key to choose a number and press **MODE** key to next 2.

Next 2, The flashing digits on the right is **ON/OFF** mode of this alarm, use **UP/DOWN** key to open or closed this alarm, **ON** is open. Then press **MODE** key to next 3
Next 3, now the flashing digits on the right is the snooze time, use **UP/DOWN** key or 0~9 to change the number. Then press **MODE** key to next 4.

Next 4, The flashing digits on the right is **ON/OFF** mode of snooze, use **UP/DOWN** key to open or close snooze, **ON** is open.

Press **RET** or  to save and exit.

2. The same way to set the other alarm.

Countdown setting:

*Support 365 days / 10 seconds countdown.

*Press **CDSET** key get into countdown setting.

***Day Hour Minute** and second is in turn and use **MODE** key to move to next position.

*Take an example:

1. Press **CDSET** key get into countdown setting.

2. 3 digits are flashing, that is days, and the max day of countdown is 365 days, use **UP/DOWN** key or 0~9 key to choose a number and press **MODE** key to next.

3. Flashing digits on the left is Hour, use **UP/DOWN** key or 0~9 key to choose a number and press **MODE** key to next.

4. Flashing digits on the right is minute, use **UP/DOWN** key or 0~9 key to choose a number and press **MODE** key to next.

5. Flashing digits on the right is second, use **UP/DOWN** key or 0~9 key to choose a number and press **MODE** key to next.

6. The flashing digits on the right is **ON/OFF** mode of countdown, use for reserve this countdown. Use **UP/DOWN** key to open or close snooze, **ON** is open.

7. When all is ok, press  key to start or pause countdown.

8. Only have 1 group of countdown. When there is days countdown, will display days first, and when days go over, will display hour and minute and the last is seconds.

9. Will rings "didi" when there is only 5 seconds last and will ring for 10 seconds when the countdown is over.

10. Press **RET** to exit countdown.

Stopwatch setting

*Press **ST** key get into stopwatch setting.

*Press  key to start or pause stopwatch.

*The max count time is 23 hour 59 minutes 59 seconds.

*Count from 0 seconds, when seconds and minutes are full of the screen, will only display minutes and hours.

*Press **RET** key to exit stopwatch.